

Eternal Lighting

ElitePar™ TRI 10 Watt RGB LEDs

USER MANUAL



ElitePar™ TRI

Professional Entertainment Equipment

Introduction:

You will be so thrilled to know a thinking green LED lighting manufacture has brought to light the missing link in lighting design for room wall wash lighting to an all new level. That missing link is in the details throughout our Research and Development phase and road testing in real world applications. Eternal Lighting made this par fixture unlike any other fixture on the market today. The impossible before is now a reality. The proprietary EliteProgramming™ & DMX control on board the ElitePar™ Quad and ElitePar™ Series in part or in its entirety is the intellectual property (IP) of Eternal Lighting LLC. Licensing for EliteProgramming™ and more information can be found by contacting Eternal Lighting with the contact form on our site. The ElitePar™ RGBA and the EliteProgramming™ Series are trademarks of Eternal Lighting LLC. EliteProgramming™ refers to the identification of the trademark itself and the functionality.

ElitePar™ TRI

Features & Technical Specifications:

- 10 Watt Ultra Bright TRI RGB LEDs
- 3CH, 4CH, 6CH
- Sound Active - (3 Different Sound Active Modes)
- Sound Active is accessible by DMX or Manual
- Auto Mode with Speed Control
- Fade mode with Speed Control
- Manual Color Mix Mode by Master Slave all other Fixtures change color on demand
- LCD Push Button Display
- Power In & Power Out
- Master Reset Function
- Total Run Hour View
- Lux 11,500 at 1 Meter
- Eternal Lighting 2.4Ghz Wireless DMX XT Stick™ Ready

Menu:

Addr: DMX Address (A000-A512)

ChNd: Channel Mode 3CH, 4CH, 6/7CH

SLNd: Slave/Master Mode (Note: Put in Mast mode when using standalone and Slav when using DMX)

ShNd:

- **SOUN:** (3 different Sound active modes)
 - S-1 ON (16-100) Color change Color Change, Fade & Strobe
 - S-2 ON (101-175) Color change when hear sound through 15 preset colors and no sound or low sound it will stop on the last color it was on until it hears sound
 - S-3 ON (176-255) Color change when hear sound & Fade when no sound or low sound
- **COLO:** AUTO Color change – Press Enter Sp 1 (very slow cycle all 31 pre-set colors) Sp 8 (very fast cycle all 31 pre-set colors)
- **Fade:** Press enter Sp1=Very Slow – Sp8=fast
- **Nanu:** Color Mixer – Red 0-255, Green 0-255, Blue 0-255
When you mix your desired color, press Enter to save the command.
(Note: When using DMX, put all colors back to 255)



NAdL: Master Dimmer for Nanu (color mixer) 0-255 brightness

Test: Press Enter to color change through Red, Green, Blue

VE 2.0: This feature displays lifetime run hours

DMX Control Instruction:

3 Channel:

Channel	Channel Values	Color
1 Channel	0-255	Red Dimmer
2 Channel	0-255	Green Dimmer
3 Channel	0-255	Blue Dimmer

6/7 Channel:

Channel	Channel Values	Function
Channel 1	0-255	All Dimmer
Channel 2	0-255	Red Color Dimmer
Channel 3	0-255	Green Color Dimmer
Channel 4	0-255	Blue Color Dimmer
Channel 5	0-255	Strobe Mode
Channel 6	000-015 Sound Off 016-100 Sound Mode 1 (S1) 101-175 Sound Mode 2 (S2) 176-255 Sound Mode 3 (S3)	Sound Mode
Channel 7	000-000 Off 001-119 Color 1 – 12 120-189 Fade (Slow to Fast) 190-239 Auto (Slow to Fast) 240-255 Sound Active(withCH7)	Show Mode

Please visit our website at www.EternalLighting.com to veiw our warranty statement. Thank you for your purchase!